


## MECHANICAL (mm)







### MOXIE NOTES:

- Operating temperature: -40°C to +85°C.
- Storage temperature: -40°C to +85°C.
- Measurement Frequency for Inductance : lkHz/l.OV
- DCR Measured on a 502BC ohm-meter
- Saturation current: Value of inductance decrease within 20%
- ullet Temperature rise current : A rise in temperature of core surface is within  $40^{\circ}\text{C}$ .
- RoHS Compliant.
- Packaging: Tape & reel.
- MoxiE Inductor Corporation custom designs are subject to United States copyright and or patent protection(s).
- MoxiE Inductor Corporation specifications are subject to change without notice.
- Tolerances unless otherwise specified: 0~10=±0.15, 10~20=±0.20, 20~40=±0.25, 40~70=±0.30, ≥70=±0.40



(888)535.5207 W

WWW-MOXIEINDUCTORS.COM

DIGITAL AMPLIFIER INDUCTOR


MOXIE MOX-DAI-0910 SERIES

PAGE 1/3

REV. -

DWG #: MOXDAID910

## PCB LAYOUT (mm)



#### MOXIE NOTES:

- Operating temperature: -40°C to +85°C.
- Storage temperature: -40°C to +85°C.
- Measurement Frequency for Inductance : lkHz/l.OV
- DCR Measured on a 502BC ohm-meter
- Saturation current: Value of inductance decrease within 20%
- Temperature rise current : A rise in temperature of core surface is within 40°C.
- RoHS Compliant.
- Packaging: Tape & reel.
- MoxiE Inductor Corporation custom designs are subject to United States copyright and or patent protection(s).
- MoxiE Inductor Corporation specifications are subject to change without notice.
- Tolerances unless otherwise specified: 0~10=±0.15, 10~20=±0.20, 20~40=±0.25, 40~70=±0.30, ≥70=±0.40



(888)535.5207 WWW.MOXIEINDUCTORS.COM

DIGITAL AMPLIFIER INDUCTOR

MOXIE MOX-DAI-0910 SERIES

PAGE 2/3

REV. -

DWG #: MOXDAID910

# ELECTRICAL @ 25°C

MOXIE PART NUMBER	INDUCTANCE (µH) ±20%	DCR (mΩ) NOMINAL	DCR (mΩ) MAX-	ISAT (A) DROP ≤20%	IRMS (A) RISE (≤40°C)
MOX-DAI-0910-6R8M	6.80	15.90	18.75	7.85	5.00
MOX-DAI-0910-8R2M	8.20	15.85	18.50	7.05	4.95
MOX-DAI-0910-100M	10.00	18.05	20.50	5.65	4.80
MOX-DAI-0910-150M	15.00	29.25	34.50	4.85	3.55
M0S-DAI-0910-220M	22.00	36.50	44.50	3.40	3.50

#### MOXIE NOTES:

- Operating temperature: -40°C to +85°C.
- Storage temperature: -40°C to +85°C.
- Measurement Frequency for Inductance : lkHz/l.OV
- DCR Measured on a 502BC ohm-meter
- Saturation current: Value of inductance decrease within 20%
- Temperature rise current : A rise in temperature of core surface is within 40°C.
- RoHS Compliant.
- Packaging: Tape & reel.
- MoxiE Inductor Corporation custom designs are subject to United States copyright and or patent protection(s).
- MoxiE Inductor Corporation specifications are subject to change without notice.
- Tolerances unless otherwise specified: 0~10=±0.15, 10~20=±0.20, 20~40=±0.25, 40~70=±0.30, ≥70=±0.40



(888)535.5207 WWW.MOXIEINDUCTORS.COM

DIGITAL AMPLIFIER INDUCTOR

MOXIE MOX-DAI-0910 SERIES

PAGE 3/3 REV. - DWG #: MOXDAIO910